


ASSEMBLY OF WALL & TOWER UNITS

STEP 1 - Level the system



1/ Start by building the **bottom section** (the floor section) of the system **only**, using the **grey junctions** with the levelling screw/foot. Place the system in the area chosen.

Check to see that the levelling screw is **fully retracted** before continuing.



2/ Start to level the system from the **highest point** of the floor. Raise the other junctions by extending the the levelling screws as required. Continue with all points until the complete bottom row is as level as possible.




3/ Place the levelling tool between two **junctions**.




4/ Do **not** place the levelling tool between two rods.

STEP 2 - Build the system up




1/ Connect rods to junctions.

Please observe!
Mount both ends at the same time




2/ Connect wings to rods.



3/ For the "inner 90 degree corners" of wall & tower units, attach magbar connectors and magbars.

STEP 3 - Attach the panels



1/ Slide "**hangers**" into slots on the **top edge** of each top wing.
2/ Attach "**clickers**" in the



bottom slots of the bottom wings, to match the position of the hangers.

3/ Slide the "**corner tabs**" at



the top of each graphic panel down into the hangers. They should fit snugly and precisely inside the hanger .

4/ The "corner tabs" at the two



bottom corners of the graphic panels should then click into **locked position** with a gentle push from the front of the panel.

5/ On a wall & tower unit **al-**



ways start with the **inner corner** panels

6/ Finish of by putting up the rest of the panels.

ACCESSORIES



Shelf kit incl. 2 support brackets



LCD screen holder



Show case



Plastic gripper (for hard panels)



Halogen spotlight, 200W



Mark Bric Display Corp.

North America
Tel. 800.742.6275 Fax 800.565.9506
E-mail: markbric@markbric.com

Mark Bric Display AB

Worldwide Headquarters
Tel. +46 (0)33 480 460 Fax +46 (0)33 480 470
E-mail: display@markbric.se

www.markbric.com

General Assembly Instructions

